

WIRING DIAGRAM SYMBOLS

Article Text

1990 Volkswagen Corrado

For Volkswagen Technical Site: <http://vw.belcom.ru>

Copyright © 1998 Mitchell Repair Information Company, LLC

Thursday, March 23, 2000 09:53PM

ARTICLE BEGINNING

WIRING DIAGRAMS

How To Use The Wiring Diagrams

INTRODUCTION

The wiring diagrams and technical service bulletins, containing wiring diagram changes, are obtained from the domestic and import manufacturers. These are checked for accuracy and are all redrawn into a consistent format for easy use.

All diagrams are arranged with the front of the vehicle at the left side of the first page and the rear of the vehicle at the right side of the last page. Accessories are shown near the end of the diagram.

Components are shown in their approximate location on the vehicle. Due to the constantly increasing number of components on vehicles today, it is impossible to show exact locations.

In the past, when cars were simpler, diagrams were simpler. All components were connected by wires, and diagrams seldom exceeded 4 pages in length. Today some wiring diagrams require more than 16 pages. It would be impractical to expect a service technician to trace a wire from page 1 across every page to page 16.

Removing some of the wiring maze reduces eyestrain and time wasted searching across several pages. Today, the majority of diagrams now follow a much improved format, which permits space for internal switch details and connector shapes.

Any wires that don't connect directly to their components are identified on the diagram to indicate where they go. There is a legend on the first page of each diagram, detailing component location. It refers you to sub-systems, using grid NUMBERS at the top and bottom of the page and grid LETTERS on each side. This grid system works in a manner similar to that of a road map.

HOW TO USE THE WIRING DIAGRAMS

1) On the first page of the diagram, you will find a listing of major electrical components or systems. Locate the specific component or system you wish to trace. A grid number and letter will follow the component's name.

2) Use the grid NUMBERS (arranged horizontally across the top and bottom of each page) to find the page of the wiring diagram that contains the component you're seeking. When you reach this page, use the grid LETTERS on the side of the page to determine the component's vertical location.

3) Locate the circuit you need to service. The internals are shown for switches and relays to assist you in understanding how the circuit operates.

NOTE: In some of the newer wiring diagram articles in this product, there is a Legend for the wiring diagrams that has

Article Text (p. 2)

For Volkswagen Technical Site: <http://vw.belcom.ru>

Thursday, March 23, 2000 09:53PM

① TEMP SENS (GND)

② BATTERY (+)

③ FUEL GAUGE (INST CLSTR)

[illegible]

Black BLK BK

WIRING DIAGRAM SYMBOLS

Article Text (p. 3)

1990 Volkswagen Corrado

For Volkswagen Technical Site: <http://vw.belcom.ru>

Copyright © 1998 Mitchell Repair Information Company, LLC

Thursday, March 23, 2000 09:53PM

Blue	BLU	BU
Brown	BRN	BN
Clear	CLR	CR
Dark Blue	DK BLU	DK BU
Dark Green	DK GRN	DK GN
Green	GRN	GN
Gray	GRY	GY
Light Blue	LT BLU	LT BU
Light Green	LT GRN	LT GN
Orange	ORG	OG
Pink	PNK	PK
Purple	PPL	PL
Red	RED	RD
Tan	TAN	TN
Voilet	VIO	VI
White	WHT	WT
Yellow	YEL	YL
AA				

WIRING DIAGRAM SYMBOL IDENTIFICATION

NOTE: Standard wiring symbols are used on diagrams. The list below will help clarify any symbols that are not easily understood at a glance. Most components are labeled "Motor", "Switch" or "Relay" in addition to being drawn with the standard symbol.

WIRING DIAGRAM SYMBOLS

Views of the symbols used in the WIRING DIAGRAM articles are in the following graphics. See Figs. 3 through 25.



Fig. 3: Circuit Breaker




Fig. 4: Coil (Internal)



Fig. 5: Connector




Fig. 6: Diode (In-Line)



Fig. 7: Diode (Internal)



Fig. 8: Diode (Light Emitting)

WIRING DIAGRAM SYMBOLS

Article Text (p. 4)

1990 Volkswagen Corrado

For Volkswagen Technical Site: <http://vw.belcom.ru>

Copyright © 1998 Mitchell Repair Information Company, LLC

Thursday, March 23, 2000 09:53PM



DEFOGGER GRID

Fig. 9: Defogger Grid



FUSE

Fig. 10: Fuse



FUSIBLE LINK

Fig. 11: Fusible Link



GROUND

Fig. 12: Ground



GLOW PLUG, RESISTOR (In-Line)
MIRROR HEATER

Fig. 13: Glow Plug Resistor (In-Line) or Mirror Heater



INJECTOR, PHOTOCCELL

Fig. 14: Injector (Diesel) or Photocell (Gasoline)



INTERNAL FUSE,
THERMAL LIMITER

Fig. 15: Internal Fuse, Thermal Limiter




LAMP (Dual Element)

Fig. 16: Lamp (Dual Element)



LAMP (Single Element)

Fig. 17: Lamp (Single Element)



MOTOR

Fig. 18: Motor



RESISTOR (Internal)

Fig. 19: Resistor (Internal)



SENSOR, THERMISTOR

Fig. 20: Sensor, Thermistor



SOLENOID

Fig. 21: Solenoid



SOLID STATE DEVICE,
TRANSISTOR

Fig. 22: Solid State Device, Transistor



SWITCH (Internal)

Fig. 23: Switch (Internal)

WIRING DIAGRAM SYMBOLS

Article Text (p. 5)

1990 Volkswagen Corrado

For Volkswagen Technical Site: <http://vw.belcom.ru>

Copyright © 1998 Mitchell Repair Information Company, LLC

Thursday, March 23, 2000 09:53PM



TWO PIN SWITCH

Fig. 24: Two Pin Switch



VARIABLE RESISTOR
OR POTENTIOMETER

Fig. 25: Variable Resistor or Potentiometer

END OF ARTICLE